



电子元器件系列(中国.厦门) China.Xiamen
www.rf-china.com RF-Micom co.,Ltd

Email:sales@rf-china.com

Telephone:0086-592-5713956 Fax:5201617

10. All units must have an external fuse provided in the end use *application. See Table 1 for ratings. Same avalues apply to IP-200 Series.

Table 1

<u>Model</u>	<u>Fuse Rating</u>
VI-27X-XX	(Buss PC-TRON) 3 A
VI-26X-XX	(Buss PC-TRON) 3 A
VI-25X-XX	(Buss PC-TRON) 5 A
VI-24X-XX	6 A/125 V
VI-23X-XX	8 A/125 V (Optional 10 A Pico II, 125 V)
VI-2NX-XX	8 A/125 V (Optional 10 A Pico II, 125 V)
VI-22X-XX	8 A/60 V
VI-2WX-XX	12 A/32 V
VI-21X-XX	12 A/32 V
VI-20X-XX	12 A/32 V
VI-2FX-XX	(Buss PC-TRON) 5 A
VI-2TX-XX	(Buss PC-TRON) 5 A

11. Secondary outputs 5 V-48 V comply with SELV requirements. Secondary 52 V - 95 V are nonSELV outputs.

12. The following Models are not provided with an Over Temperature Protective Device. Considerations should be given to ensure that the maximum temperature of the base plate does not exceed 85°C, under normal and fault conditions.

Models

VI-2N3-05, VI-2N3-06, VI-2NR-01, VI-2T4-08, VI-254-30, VI-254-31, VI-260-91, VI-260-92, VI-260-95, VI-260-97, VI-260-101, VI-261-53, VI-262-32, VI-263-24, VI-263-26, & VI-26L-10.

SPECIALS:

<u>Model</u>	<u>Parent</u>	<u>Input (DC)</u>	<u>Output (DC)</u>
VI-200-14	200-C4	9.2-36 V/3.12 A/75 W	5 V/10 A/50 W
VI-200-15	200-C4	20-85 V/1.564/75 W	5 V/10 A/50 W
VI-200-24	200-CY	9.5-28 V/6.25 A/75 W	5 V/10 A/50 W
VI-200-31	200-CX	10-25 V/8.3 A/100 W	5.0 V/15 A/75 W
VI-200-33	200-CX	10.5-20 V/9.6 A/115 W	6.5 V/10 A/65 W
VI-201-08	201-CY	9.2-36 V/3.12 A/75 W	12 V/4.2 A/50 W
VI-201-14	201-CY	10-36 V/6.25 A/75 W	12 V/4.17 A/50W
VI-201-17	201-CZ	10-55 V/4.6 A/55 W	12 V/2.5 A/30 W
VI-201-19	201-CX	10-30 V/6.67 A/100 W	12 V/6.25 A/75 W
VI-201-25	201-CY	9.2-36 V/6,25 A/75 W	12 V/4.17 A/50 W
VI-203-06	203-CX	10-32 V/4.16 A/75 W	34 V/3.12 A/75 W
VI-203-07	203-CX	12 V/8.3 A/100 W	24 V/3.1 A/75 W
VI-203-19	203-EX	10-15 V/8.33 A/100 W	24 V/4.17 A/75 W
VI-204-03	204-CX	10-20 V/10 A/100 W	54 V/1.4 A/75 W
VI-210-12	210-CW	21-32 V/6.74 A/162 W	6.5 V/21 A/137 W
VI-210-13	210-CW	21-36 V/5.2 A/125 W	5 V/20 A/100 W
VI-211-07	211-CW	21-36 V/5.2 A/125 W	12 V/8.3 A/100 W
VI-211-16	211-EV	21-32 V/7.71 A/185 W	8 V/16.88 A/135 W
VI-212-07	212-CW	21-36 V/5.2 A/125 W	15 V/6.6 A/100 W
VI-214-24	214-CY	21-32 V/4.37 A/105 W	80 V/0.63 A/50 W
VI-220-08	220-IY	18-54 V/20.8 A/75 W	5 V/3.3 A/50 W
VI-220-09	220-CW	21-56 V/3.47 A/105 W	5 V/20 A/100 W
VI-220-10	220-CW	17-42 V/5.2 A/125 W	5 V/20 A/100 W
VI-220-12	220-CW	36 V/4.16 A/135 W	5 V/20 A/100 W
VI-220-13	220-CW	36/4.16 A/135 W	5 V/20 A/100 W
VI-220-17	220-CW	21-56 V/3.75 A/135 W	5 V/20 A/100 W
VI-220-21	220-IV	20-40 V/7.14 A/200 W	5.0 V/30 A/ 250 W
VI-221-07	221-CW	21-56 V/3.47 A/125 W	12 V/8.3 A/100 W
VI-221-17	221-EX	20-72 V/2.08 A/100 W	12 V/6.25 A/75 W
VI-222-05	222-IX	18-54 V/2.77 A/100 W	15 V/5 A/75 W
VI-222-06	222-IY	18-54 V/2.08 A/75 W	15 V/3.3 A/50 W
VI-222-07	222-CY	20-85 V/1.56 A/75 W	15 V/3.3 A/50 W
VI-223-02	223-IY	18-54 V/2.08 A/75 W	24 V/2.08 A/50 W
VI-223-03	223-IW	18.54 V/3.47 A/125 W	24 V/4.17 A/100 W
VI-224-03	224-CY	20-72 V/1.94 A/70 W	60 V/.75 A/40 W
VI-230-28	230-CW	48 V/26 A/125 W	5 V/20 A/100 W
VI-230-44	23X-CU	39.5-65 V/6.9 A/335 W	5.2 V/44 A/228 W
VI-231-01	231-CU	42-60 V/4.68 A/225 W	12 V/16.6 A/220 W
VI-232-05	232-CX	48 V/2.08 A/100 W	15 V/5 A/75 W
VI-232-06	232-CV	48 V/4.16 A/200 W	15 V/10 A/150 W
VI-234-13	234-CU	42-60 V/5.2 A/250 W	55 V/3.64 A/200 W
VI-232-07	232-CU	42-60 V/4.68 A/325 W	15 V/13.3 A/200 W
VI-233-06	233-CX	42-60 V/2.08 A/100 W	24 V/3.1 A/75 W
VI-241-04	241-CY	11-72 V/1.25 V/60 W	12 V/3 A/36 W
VI-241-05	241-CY	11-72 V/1.25 A/60 W	12 V/3 A/36 W
VI-241-08	241-CY	20-72 V/1.27 A/61 W	12 V/3 A/36 W
VI-242-02	242-CW	55-100 V/1.73 A/125 W	15 V/6.64/100 W
VI-252-04	252-CU	75-150 V/204 A/225 W	28 V/7.14 A/200 W
VI-250-01	250-CV	100-200 V/1.3 A/200 W	6.5 V/23 A/150 W
VI-250-13	250-CW	150 V/0.9 A/135 W	6 V/16.7 A/100 W
VI-250-21	25T-IV	100-200 V/1.35 A/200 W	6.7 V/23 A/155 W
VI-250-22	250-EW	120-220 V/.941 A/150 W	5.0 V/20 A/100 W
VI-250-23	250-EV	100-200 V/1.37 A/200 W	6.0 V/25 A/150 W
VI-250-24	250-EV	100-200 V/1.37 A/200 W	6.0 V/25 A/150 W
VI-252-11	252-CV	60-160 V/2.6 A/200 W	15 V/10 A/150 W

<u>Model</u>	<u>Parent</u>	<u>Input (DC)</u>	<u>Output (DC)</u>
VI-254-24	254-CU	100-200 V/1.5 A/225 W	35 V/5.7 A/280 W
VI-254-30	254-EU	100-200 V/1.66 A/250 W	55 V/3.64 A/200 W
VI-254-31	254-EU	100-200 V/1.66 A/250 W	63 V/3.17 A/200 W
VI-260-09	26W-CV	200-400 V/0.67 A/200 W	5.5 V/27.5 A/150 W
VI-260-29	260-CV	300 V/0.66 A/200 W	5 V/30 A/150 W
VI-260-37	260-SV	200-400 V/.66 A/200 W	50 V/30 A/150 W
VI-260-46	260-CV	200-400 V/.66 A/200 W	5.2 V/28.8 A/150 W
VI-260-48	260-41	210-400 V/3.27 A/100 W	2 V/.37 A/74 W
VI-260-49	260-42	210-400 V/.737 A/225 W	5 V/37 A/185 W
VI-260-50	VI-260-41	210-400 V/.327 A/100 W	2 V/37 A/74 W
VI-260-51	260-43	210-400 V/.49 A/150 W	5 V/25 A/125 W
VI-260-53	260-CW	200-400 V/.416 A/125 W	5 V/20 A/100 W
VI-260-54	260-CY	200-400 V/.25 A/75 W	5 V/10 A/50 W
VI-260-57	260-CY	200-400 V/.216 A/65 W	3.4 V/11 A/37.5 W
VI-260-63	260-CV	200-400 V/.33 A/100 W	2.0 V/37 A/74 W
VI-260-64	260-CW	300 V/0.5 A/150 W	5 V/20 A/100 W
VI-260-65	260-CX	300 V/0.33 A/100 W	5 V/15 A/75 W
VI-260-66	260-CV	200-400 V/0.66 A/200 W	5 V/30 A/150 W
VI-260-67	260-CW	200-400 V/0.5 A/150 W	5 V/20 A/100 W
VI-260-68	260-22	200-400 V/0.78 A/235 W	5 V/37 A/185 W
VI-260-76	260-CV	200-400 V/0.67 A/200 W	5.2 V/28.8 A/150 W
VI-260-78	260-EY	200-400 V/0.45 A/135 W	6.3 V/15.9 A/100 W
VI-260-85	260-IU	200-400 V/0.66 A/200 W	6.0 V/30 A/180 W
VI-260-88	260-EU	240-400 V/0.83 A/250 W	6.5 V/30 A/195 W
VI-260-89	26X-CU	250-400 V/0.75 A/278.8 W	5.2 V/44 A/228.8 W
VI-260-91	26Z-IV	200-400 V/0.28 A/85 W	2.0 V/30 A/60 W
VI-260-92	260-IU	200-400 V/0.83 A/250 W	5.0 V/40 A/200 W
VI-260-93	260-IV	200-400 V/0.66 A/200 W	5.0 V/30 A/150 W
VI-260-94	261-CU	200-400 V/0.66 A/200 W	8.0 V/21 A/168 W
VI-260-95	26V-EV	200-400 V/0.66 A/200 W	5.8 V/25.8 A/150 W
VI-260-96	260-EU	240-400 V/0.83 A/250 W	8.0 V/25 A/200 W
VI-260-97	260-CU	200-400 V/0.83 A/250 W	5.0 V/40 A/200 W
VI-260-98	260-CU	200-400 V/0.75 A/225 W	5.0 V/35 A/175 W
VI-260-101	26V-EV	200-400 V/0.66 A/200 W	5.8 V/25.8 A/150 W
VI-260-102	260-CU	200-400 V/0.83 A/250 W	5.0 V/40 A/200 W
VI-260-103	260-CV	200-400 V/0.66 A/200 W	5.0 V/30 A/150 W
VI-260-CV	260-07	300 V/0.66 A/200 W	5.8 V/25.8 A/150 W
VI-261-27	261-CY	200-400 V/2.5 A/75 W	12 V/4.16 A/50 W
VI-261-30	261-CV	200-400 V/.66 A/200 W	8 V/18.75 A/150 W
VI-261-31	261-CV	200-400 V/.75 A/225 W	8.6 V/19.3 A/166 W
VI-261-32	261-CX	300 V/0.33 A/100 W	12 V/6.25 A/75 W
VI-261-33	261-CU	300 V/0.75 A/225 W	12 V/16.6 A/200 W
VI-261-34	261-CW	300 V/4.16 A/125 W	12 V/8.3 A/100 W
VI-261-35	261-CV	300 V/0.66 A/200 W	12 V/12.5 A/150 W
VI-261-40	261-CW	200-400 V/0.33 A/100 W	8 V/9 A/72 W
VI-261-52	261-CW	200-400 V/0.83 A/250 W	12 V/16.67 A/200 W
VI-261-53	261-CW	200-400 V/0.5 A/150 W	12 V/8.3 A/100 W
VI-262-15	262-CY	200-400 V/.25 A/75 W	15 V/3.3 A/50 W
VI-262-21	262-CY	170-270 V/1.125 A/225 W	13.5 V/14.8 A/200 W
VI-262-25	262-CV	140-260 V/1.05 A/200 W	13.5 V/12 A/162 W
VI-262-27	262-CU	200-400 V/0.83 A/250 W	20 V/10 A/200 W
VI-262-28	262-CV	140-260 V/1.05 A/200 W	13.5 V/12 A/162 W
VI-262-31	262-EX	200-400 V/0.45 A/135 W	16.5 V/4.5 A/75 W
VI-262-32	262-CU	200-400 V/0.83 A/250 W	15 V/13.3 A/200 W
VI-262-33	262-CX	200-400 V/0.45 A/135 W	15 V/5 A/75 W
VI-262-37	262-CV	200-400 V/0.66 A/200 W	15 V/10 A/150 W
VI-263-07	263-CY	200-400 V/.25 A/75 W	24 V.2.08 A/50 W

<u>Model</u>	<u>Parent</u>	<u>Input (DC)</u>	<u>Output (DC)</u>
VI-263-08	263-CV	200-400 V/.66 A/200 W	24 V/6.25 A/150 W
VI-263-10	263-CU	300 V/0.75 A/225 W	24 V/8.3 A/200 W
VI-263-11	263-CV	300 V/0.66 A/200 W	24 V/6.25 A/150 W
VI-263-12	263-CV	200-400 V/0.66 A/200 W	24 V/6.25 A/150 W
VI-263-13	263-CU	240-400 V/0.75 A/225 W	24 V/8.3 A/200 W
VI-263-14	263-CW	200-400 V/0.46 A/139 W	26 V/4 A/104 W
VI-263-23	26J-EU	200-400 V/0.74 A/221 W	36 V/4.75 A/171 W
VI-263-24	263-EV	200-400 V/0.66 A/200 W	24 V/6.25 A/150 W
VI-263-26	263-CU	200-400 V/0.83 A/250 W	24 V/8.33 A/200 W
VI-263-27	263-EV	200-400 V/0.66 A/200 W	5.2 V/44 A/228.8 W
VI-263-28	263-CU	200-400 V/0.83 A/250 W	24 V/8.33 A/200 W
VI-264-01	26H-CU	170-270 V/1.125 A/225 W	54 V/3.70 A/200 W
VI-264-08	264-CU	200-400 V/.75 A/225 W	95 V/2.10 A/200 W
VI-264-17	264-08	200-400 V/.75 A/225 W	95 V/2.10 A/200 W
VI-264-20	264-CU	200-400 V/.65 A/195 W	36 V/4.7 A/170 W
VI-264-21	264-CU	200-400 V/1.13 A/225 W	55 V/3.6 A/200 W
VI-264-23	264-CU	200-400 V/0.75 A/225 W	35 V/5.7 A/200 W
VI-264-28	264-CU	200-400 V/4.09 A/225 W	55 V/3.64 A/220 W
VI-264-38	264-EV	200-400 V/0.67 A/200 W	56 V/2.68 A/150 W
VI-264-46	264-EU	200-400 V/0.83 A/250 W	48 V/4.17 A/200 W
VI-26L-03	26L-CU	200-400 V/1.4 A/420 W	28 V/8.03 A/225 W
VI-26L-04	26L-CU	200-400 V/1.25 A	28 V/7.14 A/200 W
VI-26L-08	26L-IV	200-400 V/0.66 A/200 W	28 V/5.36 A/150 W
VI-26L-09	26L-IU	200-400 V/0.83 A/250 W	28 V/7.14 A/200 W
VI-26L-10	26L-EU	200-400 V/0.83 A/250 W	28 V/7.14 A/200 W
VI-270-02	270-EX	145-358 V/0.54 A/135 W	5 V/20 A/100 W
VI-271-01	271-CW	130-375 V/0.46 A/140 W	10.5 V/10 A/105 W
VI-2N0-08	2N0-CV	36-76 V/2.85 A/137 W	6 V/17 A/102 W
VI-2N0-09	2N0-CV	38-72 V/4.16 A/200 W	5.4 V/27.7 A/150 W
VI-2N0-10	2N0-CV	36-76 V/2.85 A/137 W	6 V/17 A/102 W
VI-2N0-11	2N0-CU	36-76 V/4.38 A/210 W	5.5 V/29.09 A/160 W
VI-2W0-07	2W0-CW	18-36 V/5.63 A/135 W	5 V/20 A/100 W
VI-2W1-01	2W1-CW	18-36 V/5.63 A/135 W	8 V/12.5 A/100 W
VI-2W1-03	2W3-CV	18-36 V/8.3 A/200 W	12 V/12.5 A/150 W
VI-2WF-01	2WF-CU	21-36 V/10.41 A/250 W	72 V/2.78 A/200 W
VI-2WL-02	2WL-IV	18.36 V/8.33 A/200 W	28 V/5.36 A/150 W
VI-274-01	274-CY	100-375 V/.25 A/75 W	61 V/.819 A/50 W
VI-2NY-02	2NY-IV	36-76 V/2.79 A/134 W	3.3 V/30 A/99 W
VI-2NO-02	2NO-CV	38-72 V/4.16 A/200 W	54 V/27.7 A/150 W
VI-2NO-03	2NO-CV	36-76 V/4.16 A/200 W	6.3 V/23.8 A/150 W
VI-2NO-04	2NO-CW	36-76 V/3.125 A/150 W	5 V/20 A/100 W
VI-2NO-16	2NO-IV	36-76 V/4.16 A/200 W	5.7 V/26.3 A/150 W
VI-2NO-19	2NO-CV	36-76 V/4.16 A/200 W	5.5 V/30 A/165 W
VI-2NO-25	2N0-EW	36-76 V/2.81 A/135 W	5 V/20 A/100 W
VI-2N2-01	2N2-CY	36-76 V/1.04 A/50 W	15 V/1.6 A/25 W
VI-2N3-04	2N3-CU	32-60 V/5.20 A/250 W	24 V/8.33 A/200 W
VI-2N3-05	2N3-CU	36-72 V/5.20 A/250 W	24 V/8.33 A/200 W
VI-2N3-06	2N3-TW	30-90 V/1.81 A/109 W	24 V/3.5 A/84 W
VI-2N4-07	2N4-CU	36-76 V/5.8 A/280 W	48 V/4.17 A/200 W
VI-2NR-01	2NR-EV	36-72 V/4.16 A/200 W	7.5 V/20 A/150 W
VI-2WO-01	2WO-CW	18-36 V/6.25 A/135 W	5 V/20 A/100 W
VI-2WO-02	2WO-CV	16-32 V/8.3 A/200 W	5 V/30 A/150 W
VI-2W2-01	2W2-CV	16-32 V/8.3 A/200 W	15 V/10 A/150 W
VI-B00-01	B00-CY	20-85 V/6.25 A/75 W	5 V/10 A/50 W
VI-B03-04	B03-CX	10-32 V.8.33 A/100 W	24 V/3.12 A/75 W
VI-B03-04	B20-CW	21-56 V/3.47 A/125 W	5 V/20 A/100 W
VI-B11-02	B11-EV	21-32 V/7.7 A/1.85 W	8.0 V/16.88 A/135 W

<u>Model</u>	<u>Parent</u>	<u>Input (DC)</u>	<u>Output (DC)</u>
VI-B20-02	B20-CW	21-56 V/3.47 A/125 W	5 V/20 A/100 W
VI-B22-01	B22-CY	20-85 V/1.56 A/75 W	15 V/3.3 A/50 W
VI-B30-16	B3X-CU	39-65 V/5.79 A/278 W	5.2 V/44 A/228.8 W
VI-B32-01	B32-CV	42-60 V/4.16 A/200 W	15 V/10 A/150 W
VI-B60-13	B60-CV	300 V/0.66 A/200 W	5 V/30 A/150 W
VI-B60-22	B60-18	210-400 V/.327 A/100 A	2 V/37 A/74 W
VI-B60-23	B60-19	210-400 V/.737 A/2.25 W	5 V/37 A/185 W
VI-B60-24	B60-19	210-400 V/.737 A/225 W	5 V/37 A/185 W
VI-B60-25	B60-18	210-400 V/.327 A/100 W	2 V/37 A/74 W
VI-2N0-19	2N0-CV	36-76 V/4.16 A/200 W	5.5 V/30 A/165 W
VI-2N0-25	2N0-EW	36-76 V/2.81 A/135 W	5 V/20 A/100 W
VI-B60-26	B60-CW	200-400 V/.416 A/125 W	5 V/20 A/100 W
VI-B60-27	B60-CV	200-400 V/.66 A/200 W	5 V/30 A/150 W
VI-B60-30	B60-CV	200-400 V/1.0 A/200 W	5 V/30.0 A/150 W
VI-B60-39	B60-IU	200-400 V/0.66 A/200 W	6.0 V/30 A/180 W
VI-B60-41	B6X-CU	250-400 V/0.75 A/278.8 W	5.2 V/44 A/228.8 W
VI-B60-42	B61-CU	200-400 V/0.66 A/200 W	8.0 V/21 A/168 W
VI-B60-43	B60-CU	200-400 V/0.75 A/225 W	5.0 V/36 A/175 W
VI-B60-44	B60-CU	200-400 V/0.83 A/250 W	5.0 V/40 A/200 W
VI-B61-08	B61-CU	200-400 V/1.13 A/225 W	12 V/6.25 A/200 W
VI-B61-06	B61-CU	200-400 V/.75 A/225 W	12 V/16.6 A/200 W
VI-B61-13	B61-CU	200-400 V/0.833 A/250 W	12 V/16.67 A/200 W
VI-B61-15	B61-CU	220-400 V/0.833 A/250 W	12 V/16.7 A/200 W
VI-B62-03	B62-CU	200-400 V/.75 A/225 W	15 V/13.3 A/200 W
VI-B62-05	B62-CU	170-270 V/1.125 A/225 W	13.5 V/14.8 A/200 W
VI-B62-13	B62-CU	200-400 V/0.83 A/250 W	14.4 V/13.8 A/200 W
VI-B62-14	B62-CU	200-400 V/0.83 A/250 W	15 V/13.3 A/200 W
VI-B63-02	B63-CU	200-400 V/.75 A/225 W	24 V/8.33 A/200 W
VI-B63-03	B63-EU	200-400 V/0.833 A/250 W	20 V/10 A/200 W
VI-B64-01	B64-CU	220-400 V/.75 A/225 W	95 V/2.10 A/200 W
VI-B64-04	B64-CU	200-400 V/.75 A/225 W	40 V/5 A/200 W
VI-B64-08	B64-CU	200-400 V/1.13 A/225 W	55 V/3.6 A/200 W
VI-B6H-01	B6H-CU	170-270 V/1.125 A/225 W	54 V/3.7 A/200 W
VI-B6L-01	B6L-CU	200-400 V/1.25 A	28 V/7.14 A/200 W
VI-B6L-04	B6L-IV	200-400 V/0.667 A/200 W	28 V/5.36 A/150 W
VI-B6L-05	B6L-EU	200-400 V/0.83 A/250 W	28 V/7.14 A/200 W
VI-BWO-01	BWO-CW	18-36 V/6.25 A/135 W	5 V/20 A/100 W
VI-BNO-02	BNO-CV	34-76 V/175 W	5 V/30 A/150 W
VI-260-01	260-CV	300 V/150 W	6.5 V/130 W
-06	260-CV	300 V/200 W	5 V/150 W
-22	260-CV	300 V/225 W	5 V/185 W
-23	260-CV	300 V/100 W	2 V/74 W
-24	260-CV	300 V/210 W	5 V/175 W
-26	260-CV	300 V/200 W	5 V/150 W
-27	260-CV	300 V/200 W	6 V/150 W
-31	260-CV	300 V/200 W	5 V/150 W
-33	260-CV	300 V/200 W	5 V/150 W
-34	260-CY	300 V/75 W	5 V/50 W
-41	260-23	300 V/100 W	2 V/74 W
-42	260-22	300 V/225 W	5 V/185 W
-43	260-26	300 V/150 W	5 V/125 W
VI-261-01	261-CV	300 V/200 W	12 V/150 W
-02	261-CV	300 V/200 W	12 V/150 W
-06	261-CV	300 V/135 W	12 V/100 W
-07	261-CW	300 V/75 W	12 V/50 W
-18	261-CY	300 V/220 W	12 V/200 W
-20	261-CU	300 V/135 W	12 V/100 W

<u>Model</u>	<u>Parent</u>	<u>Input (DC)</u>	<u>Output (DC)</u>
-6101	261-CW	300 V/200 W	5 V/150 W
-6002	261-CW	300 V/200 W	12 V/150 W
VI-B60-01	B60-CV	300 V/150 W	6.5 V/130 W
-06	B60-CV	300 V/200 W	5 V/150 W
-07	B60-CV	270 V/150 W	6.5 V/130 W
-11	B60-CV	300 V/100 W	2 V/74 W
-12	B60-CV	270 V/225 W	5 V/185 W
-18	B60-11	300 V/100 W	2 V/74 W
-19	B60-12	300 V/225 W	5 V/185 W
-32	B60-CV	300 V/200 W	5 V/150 W
VI-B01-02	B01-CY	12 V/200 W	5 V/150 W
VI-233-01	233-IV	48 V/200 W	24 V/150 W
VI-230-29	230-CV	42-48 V/4.32 A/207 W	6.3 V/25 A/157 W
VI-260-69	260-CV	200-400 V/.69 A/207 W	6.3 V/25 A/157 W
VI-260-71	260-CV	200-400 V/0.6 A/200 W	5 V/30 A/150 W
VI-261-36	261-CU	200-400 V/.75 A/225 W	12 V/16.6 A/200 W
VI-261-46	261-EW	200-400 V/0.5 A/150 W	9 V 11.11 A/100 W
VI-261-47	261-CU	200-400 V/0.833 A/250 W	12 V/16.67 A/200 W
VI-261-48	261-CV	250-400 V/0.65 A/220 W	9 V/18.89 A/170 W
VI-262-22	262-CV	130-300 V/.76 A/200 W	15 V/10 A/150 W
VI-264-19	264-CV	200-400 V/.66 A/200 W	62 V/2.4 A/150 W
VI-26L-02	26L-CW	130-300 V/0.465 A/121 W	24 V/4 A/96 W
VI-2N0-05	2N0-CV	36-76 V/4.16 A/200 W	5.5 V/27.2 A/150 W
VI-2N1-03	2N1-EX	36-76 V/2.35 A/113 W	12 V/5.3 A/63 W
VI-2N1-04	2N1-EY	36-76 V/1.08 A/52 W	12 V/2.67 A/32 W
VI-2N1-06	2N1-CV	36-76 V/3.75 A/180 W	12 V/10.83 A/130 W
VI-2W3-01	2W30CV	18-36 V/8.3 A/200 W	24 V/6.2 A/150 W
VI-2W4-07	2W4-CV	18-36 V/8.33 A/200 W	54 V/2.78 A/150 W
VI-26V-CV	260-07	200-400 V/.66 A/200 W	5.8 V/25.8 A/150 W
VI-2T0-02	2TY-CV	77-138 V/1.65 A/182 W	3.3 V/40 A/132 W
VI-2T0-04	2T0-1X	62-150 V/1.0 A/100 W	5 V/15 A/75 W
VI-2T0-05	2T0-1X	62-150 V/.85 A/85 W	5.0 V/12 A/60 W
VI-2T0-06	2T0-1W	62-150 V/.93 A/93 W	5.0 V/13.6 A/68 W
*VI-2T-02-07	2T1-CV	66-160 V/2.0 A/200 W	12 V/ 12.5 A/150 W
VI-2T4-07	2T4-1U	67-150 V/2 A/200 W	52 V/2.89 A/150 W
VI-2T4-03	2T4-1W	67-150 V/.95 A/105 W	52 V/1.54 A/80 W
VI-2T4-08	2T4-CV	66-160 V/2 A/200 W	48 V/3.13 A/150 W
VI-2TB-01	2TB-EV	66-145 V/1.90 A/200 W	95 V/1.58 A/150 W
VI-2T0-CV	2T0-CV	100 V/2.8 A/280	5 V/300 A/150 W
VI-B03-08	B03-CY	9.6-36 V/ 6.25 A/75 W	21 V/2.38 A/50 W
VI-B04-01	B04-CX	10-20 V/8.3 A/100 W	54 V/1.3 A/75 W
VI-B30-08	B30-CV	42-60 V/4.3 A/207 W	6.3 V/25 A/157 W
VI-B60-03	B60-CV	200-400 V/.69 A/207 W	6.3 V/25 A/157 W
VI-B61-07	B61-CU	200-400 V/.75 A/225 W	12 V/16.6 A/200 W
VI-B62-06	B61-CV	130-300 V/.76 A/200 W	15 V/10 A/150 W
VI-B62-09	B62-CV	140-260 V/1.12 A/212 W	13.5 V/12 A/162 W
VI-B62-11	B62-CU	200-400 V/0.83 A/250 W	20 V/10 A/200 W
VI-B64-13	B64-CU	200-400 V/0.83 A/250 W	48 V/4.16 A/200 W
VI-BN0-03	BN0-CV	36-76 V/4.16 A/200 W	5.5 V/27.27 A/150 W
VI-BN0-04	BN0-CU	36-76 V/4.38 A/210 W	5.5 V/29.09 A/160 W
VI-BN0-05	BN1-EV	36-76 V/3.57 A/200 W	8.0 V/17.7 A/150 W
VI-BW0-03	BW0-CW	18-76 V/5.63 A/135 W	5 V/20 A/100 W
VI-BW4-04	BW4-CV	18-36 V/8.3 A/200 W	65 V/2.5 A/162.5 W
*VI-BW4-02	BT1-CV	66-160 V/2.0 A/200 W	12 V/ 12.5 A/150 W
VI-B30-10	B30-CV	42-68 V/4.89 A/235	5.1 V/34 A/173 W
VI-B31-CV	B31-CV	42-68 V/4.33 A/208	12.5 V/12.5 A/157 W
VI-22M-02	22M-CW	18-56 V/3.75 A/135 W	10 V/10 A/100 W
VI-26M-03	26M-CW	200-400 V/0.5 A/150 W	10 V/10 A/100 W
VI-26X-01	26X-CV	200-400 V/0.66 A/200 W	5.2 V/28.8 A/150 W
VI-26X-02	26X-CU	200-400 V/0.6 A/200 W	5.2 V/25 A/130 W

SPECIALS:

<u>Model</u>	<u>Parent</u>	<u>Input (DC)</u>	<u>Output (DC)</u>
VI-201-26	201-EX	10-20 V/8.3 A/100 W	12 V/6.25 A/50 W
VI-202-13	202-CX	11.5-20 V/11.6 A/140 W	15 V/6 A/90 W
VI-203-13	203-CY	9.5-36 V/3.125 A/75 W	21 V/2.38 A/50 W
VI-203-25	203-EX	10-36 V/8.3 A/100 W	24 V/3.13 A/7 W
VI-20L-04	20L-CX	10-22 V/11.25 A/135 W	30 V/2.83 A/85 W
VI-204-09	204-CX	10-30 V/8.3 A/100 W	48 V/1.56 A/75 W
VI-2W0-12	2W0-CY	15-36 V/3.125 A/75 W	5 V/10 A/50 W
VI-2W0-13	2W0-CX	16.8-34 V/4.16 A/100 W	5 V/15 A/75 W
VI-2W1-04	2W1-XC	18-40 V/4.16 A/100 W	12 V/6.25 A/75 W
VI-2W1-12	2W1-CX	15-36 V/4.16 A/100 W	12 V/6.25 A/75 W
VI-2W4-08	2W4-CV	16.8-30 V/8.3 A/200 W	48 V/3.65 A/175 W
VI-2WY-01	2WY-CV	16.8-30 V/4.16 A/100 W	3 V/25 A/75 W
VI-210-22	210-CY	21-32 V/3.125 A/75 W	5 V/10 A/50 W
VI-210-29	210-EV	21-32 V/8.335 A/200 W	5 V/30 A/150 W
VI-211-09	211-CY	10-36 V/2.9 A/61 W	12 V/3 A/36 W
VI-211-15	211-CW	21-32 V/5.625 A/135 W	12 V/8.3 A/100 W
VI-212-09	212-CY	13-36 V/3.125 A/75 W	15 V/3.33 A/50 W
VI-212-11	212-CY	21-32 V/3.125 A/75 W	15 V/3.33 A/50 W
VI-220-11	220-CX	18-62 V/2.08 A/75 W	5.0 V/10 A/50 W
VI-220-16	220-CW	21-56 V/3.75 A/135 W	6.3 V/15.8 A/100 W
VI-221-14	221-CW	21-56 V/3.75 A/135 W	12 V/8.3 A/100 W
VI-221-18	221-CW	20-55 V/7.29 A/175 W	12 V/10.42 A/125 W
VI-221-19	221-EX	19-60 V/2.77 A/100 W	12 V/5083 A/70 W
VI-221-20	221-CW	20-60 V/3.75 A/135 W	12 V/8.3 A/100 W
VI-22L-02	22L-CW	21-56 V/3.75 A/135 W	28.3 V/3.53 A/100 W
VI-22L-04	22L-CW	20-100 V/1.88 A/135 W	28 V/3.57 A/100 W
VI-224-01	224-CW	21-56 V/3.75 A/135 W	48 V/2.08 A/100 W
VI-22M-04	22M-CW	20-60 V/3.125 A/150 W	10.5 V/12 A/126 W
VI-230-01	220-CV	48-60 V/4.16 A/200 W	6.5 V/23./150 W
VI-230-10	230-CW	40-60 V/2.81 A/135 W	5.4 V/18.52 A/100 W
VI-230-12	230-CV	42-60 V/4.08 A/196 W	6.5 V/22.34 A/146 W
VI-230-14	230-IV	42-60 V/4.16 A/200 W	5 V/30 A/150 W
VI-230-38	230-CV	42-60 V/4.42 A/212 W	6.5 V/25 A/162 W
VI-230-39	230-CU	42-60 V/2.04 A/98 W	1.2 V/40 A/48 W
VI-230-45	230-CW	42-60 V/2.81 A/135 W	5.4 V/18.52 A/100 W
VI-230-46	230-EV	42-60 V/4.16 A/200 W	5 V/30 A/150 W
VI-230-47	230-CW	42-60 V/2.81 A/135 W	5.15 V/19.42 A/100 W
VI-230-49	230-EU	42-60 V/4.16 A/250 W	5 V/40 A/200 W
VI-231-02	231-CV	42-60 V/4.16 A/200 W	12 V/12.5 A/150 W
VI-231-07	231-CY	42.60 V/0.416 A/20 W	12 V/0.83 A/10 W
VI-231-09	231-CV	42-60 V/4.16 A/200 W	12 V/12.5 A/150 W
VI-231-15	231-CU	42-60 V/502 A/250 W	12 V/16.67 A/200 W
VI-234-09	234-CU	42-60 V/5.2 A/250 W	55/3.64 A/200 W
VI-23X-01	23X-CU	39.5-660 V/6.88 A/330 W	5.2/44 A/228 W
VI-23Y-01	23Y-EV	42-60 V/2.81 A/135 W	3.3 V/30 A/99 W
VI-23Z-01	23Z-CU	42-60 V/2.08 A/100 W	2/40 A/80 W
VI-2N0-28	2N0-CY	30-76 V/1.56 A/75 W	5 V/10 A/50 W
VI-2N1-08	2N1-CY	36-76 V/1.56 A/75 W	12 V/4.17 A/50 W
VI-2N1-09	2N1-CY	30-76 V/2.08 A/100 W	12 V/6.25 A/75 W
VI-2N1-10	2N1-CU	36-76 V/0.52 A/250 W	16.674.17 A/200 W
VI-2N2-02	2N2-CY	31-60 V/1.56 A/75 W	15 V/3.33 A/50 W
VI-2N2-03	2N2-CX	31-60 V/2.08 A/100 W	15 V/5 A/75 W

<u>Model</u>	<u>Parent</u>	<u>Input (DC)</u>	<u>Output (DC)</u>
VI-2N3-02	2N3-CY	31-60 V/1.52 A/73 W	24 V/2.01 A/48 W
VI-2N3-08	2N3-TW	30-90 V/1.81 A/109 W	24 V/3.5 A/84 W
VI-2NL-03	2NL-CU	36-72 V/5.21 A/250 W	32 V/6.25 A/200 W
VI-2N4-06	2N4-CU	36-76 V/5.21 A/250 W	52.2 V/3.8 A/200 W
VI-2N4-07	2N4-CU	36-76 V/5.21 A/250 W	48 V/4.17 A/200 W
VI-2NB-01	2NB-CX	36-76 V/2.08 A/100 W	95 V/0.79 A/75 W
VI-243-02	243-IU	65-143 V/35.8 A/250 W	24 V/8.33 A/200 W
VI-243-03	243-IY	55-100 V/1.04 A/75 W	42 V/1.04 A/50 W
VI-2T0-01	2T0-IX	62-150 V/.85 A/85 W	5.0 V/12 A/60 W
VI-2T4-09	2T4-CV	77-138 V/2.27 A/250 W	48 V/4.17 A/200 W
VI-250-15	250-CY	80-10 V/0.45 A/50 W	5.0 V/5 A/25 W
VI-250-26	250-CW	100-200 V/0.9 A/135 W	5.4 V/18.52 A/100 W
VI-250-27	250-CV	100-200 V/1.37 A/200 W	6.0 V/25 A/150 W
VI-251-09	251-CU	150-250 V/1.25 A/250 W	12 V/16.66 A/200 W
VI-252-06	252-CV	75-200 V/1.37 A/200 W	15 V/10 A/150 W
VI-253-15	253-CW	150-175 V/0.62 A/100 W	20 V/4.2 A/84 W
VI-254-29	254-CU	100-200 V/1.66 A/250 W	54 V/3.7 A/200 W
VI-260-11	260-CV	200-400 V/0.66 A/200 W	5 V/30 A/150 W
VI-260-19	260-CV	200-400 V/0.66 A/200 W	5.0 V/30 A/150 W
VI-260-75	26Z-IV	200-400 V/0.28 A/85 W	2.0 V/30 A/60 W
VI-260-77	260-CU	200-400 V/0.83 A/250 W	5.0 V/40 A/200 W
VI-260-110	260-IV	200-400 V/0.66 A/200 W	5.0 V/30 A/150 W
VI-260-113	260-EU	240-400 V/0.83 A/250 W	8.0 V/25 A/200 W
VI-261-10	261-IV	200-400 V/0.66 A/200 W	12 V/12.5 A/150 W
VI-261-11	261-CW	200-400 V/0.45 A/135 W	12 V/8.3 A/100 W
VI-261-55	261-CU	200-400 V/0.83 A/250 W	12 V/16.67 A/200 W
VI-261-56	261-EU	200-400 V/0.83 A/250 W	8 V/25 A/200 W
VI-261-57	261-IW	200-400 V/0.45 A/135 W	12 V/8.3 A/100 W
VI-262-04	262-CU	200-400 V/0.83 A/250 W	15 V/13.3 A/200 W
VI-262-38	262-CU	200-400 V/0.45 A/135 W	15 V/6.66 A/100 W
VI-262-39	262-CV	200-400 V/0.66 A/200 W	15/10 A/150 W
VI-263-02	263-CU	200-400 V/0.83 A/250 W	24 V/8.33 A/200 W
VI-263-29	263-CW	200-400 V/0.45 A/135 W	24 V/4.17 A/100 W
VI-263-30	263-CU	200-400 V/0.86 A/258 W	25 V/8.33 A/208 W
VI-26L-04	26L-CU	200-400 V/0.83 A/250 W	28 V/7.14 A/200 W
VI-26L-05	26L-CU	200-400 V/0.83 A/250 W	26 V/7.69 A/200 W
VI-264-05	264-CU	200-400 V/0.83 A/250 W	48 V/4.17 A/200 W
VI-264-07	264-CV	200-400 V/0.58 A/175 W	90 V/1.5 A/135 W
VI-264-16	264-CU	200-400 V/0.83 A/250 W	62 V/3.23 A/200 W
VI-264-33	264-CU	200-400 V/0.83 A/250 W	62 V/3.23 A/200 W
VI-26F-01	26F-EU	200-400 V/0.83 A/250 W	60 V/3.33 A/200 W
VI-26R-01	26R-EU	200-400 V/0.66 A/250 W	7.5 V/26.67 A/200 W
VI-26T-05	26T-CU	210-400 V/0.83 A/250 W	6.5 V/30.77 A/200 W
VI-26X-03	26X-CU	200-400 V/1.08 A/400 W	5.2 V/44 A/228 W
VI-270-01	270-EW	145-330 V/0.54 A/135 W	5 V/20 A/100 W
VI-273-03	273-IW	100-375 V/0.54 A/135 W	24 V/4.17 A/100 W
VI-273-04	273-CW	85-375 V/0.6 A/150 W	24 V/5 A/120 W

<u>Model</u>	<u>Parent</u>	<u>Input (DC)</u>	<u>Output (DC)</u>
VI-B01-03	B01-EX	10-20 V/8.33 A/100 W	12 V/6.25 A/75 W
VI-B02-02	B02-CY	10-30 V/6.25 A/75 W	15 V/3.33 A/50 W
VI-B03-10	B03-CX	10-36 V/8.33 A/100 W	24 V/3.13 A/75 W
VI-B04-03	B04-CX	10-30 V/8.3 A/100 W	48 V/1.56 A/75 W
VI-BW4-02	BW4-CV	18-36 V/8.3 A/200 W	48 V/3.13 A/150 W
VI-B20-03	B20-CY	18-62 V/4.16 A/75 W	5 V/10 A/50 W
VI-B30-14	B30-CU	42-60 V/1.56 A/75 W	1.2 V/40 A/48 W
VI-B30-17	B30-CV	42-60 V/4.16 A/200 W	5.15 V/30 A/154 W
VI-B30-19	B30-CW	42-60 V/3.125 A/150 W	5.15 V/19.42 A/100 W
VI-B34-01	B34-CU	42-60 V/5.20 A/250 W	55 V/3.64 A/200 W
VI-B3X-01	B3X-CU	39.5-65 V/5.20 A/250 W	5.2 V/44 A/228 W
VI-B3Y-02	B3Y-EV	42-60 V/3.125 A/150 W	3.3 V/30 A/100 W
VI-BNL-02	BN1-CV	36-76 V/3.57 A/200 W	28 V/5.3 A/150 W
VI-B43-02	B43-CU	65-143 V/35.8 A/250 W	24 V/8.33 A/200 W
VI-B60-08	B60-CV	200-400 V/0.66 A/200 W	5 V/30 A/150 W
VI-B60-39	B61-CU	200-400 V/0.66 A/200 W	8.0 V/21 A/168 W
VI-B60-47	B60-FV	240-400 V/0.83 A/250 W	8.0 V/36 A/200 W
VI-B61-03	B61-CV	190-400 V/0.66 A/200 W	12.5 V/12.56 A/157 W
VI-B61-16	B61-EU	240-400 V/0.83 A/250 W	8 V/25 A/200 W
VI-B62-13	B62-CU	200-400 V/0.83 A/250 W	14.4 V/13.8 A/200 W
VI-B63-05	B63-EU	200-400 V/0.83 A/250 W	25 V/8.33 A/208 W
VI-B6L-01	B6L-CU	200-400 V/0.83 A/250 W	28 V/7.14 A/200 W
VI-B6L-02	B6L-CU	200-400 V/0.83 A/250 W	26 V/7.69 A/200 W
VI-B64-11	B64-CU	200-400 V/0.83 A/250 W	55 V/3.64 A/200 W
VI-B6F-01	B6F-EU	200-400 V/0.83 A/250 W	60 V/3.33 A/200 W
VI-B6T-02	B6T-CU	210-400 V/0.83 A/250 W	6.5 V/30.77 A/200 W
VI-B6X-01	B6X-CU	250-400 V/0.67 A/250 W	5.2 V/44 A/228 W
VI-J00-15	J00-EZ	9.8-36 V/4.16 A/50 W	5 V/5 A/25 W
VI-J00-19	J00-IZ	9.6-15 V/4.16 A/50 W	5 V/5 A/25 W
VI-J01-17	J01-EZ	9.8-36 V/4.16 A/50 W	12 V/2.08 A/25 W
VI-J04-04	J04-CY	10-23 V/6.25 A/75 W	48 V/1.04 A/50 W
VI-J04-07	J04-EY	10-20 V/6.25 A/75 W	75 V/0.67 A/50 W
VI-J10-05	J10-CX	21-32 V/3.572 A/100 W	5 V/15 A/75 W
VI-J11-05	J11-CW	21-32 V/5.62 A/135 W	10 V/10 A/100 W
VI-J11-07	J11-CW	21-32 V/5.62 A/135 W	9 V/11.1 A/100 W
VI-JW0-01	JW0-CY	13-40 V/2.3 A/55 W	5.0 V/6 A/30 W
VI-JW0-02	JW0-CZ	18-36 V/3.125 A/75 W	6 V/8.33 A/50 W
VI-JW0-06	JW0-CY	18-36 V/3.125 A/75 W	5.0 V/10 A/50 W
VI-JW1-01	JW1-CY	18-36 V/3.125 A/75 W	12 V/4.17 A/50 W
VI-JW2-01	JW2-CX	18-36 V/4.16 A/100 W	15 V/5 A/75 W
VI-JW2-04	JW2-IY	18-36 V/3.125 A/75 W	15 V/3.33 A/50 W
VI-JWL-03	JWL-IW	18-36 V/5.62 A/135 W	30 V/3.33 A/100 W
VI-JW4-02	JW4-IY	18-36 V/3.13 A/75 W	65 V/.77 A/50 W
VI-J20-18	J20-CY	22-60 V/2.08 A/75 W	6.5 V/7.6 A/50 W
VI-J21-05	J21-CY	21-56 V/2.08 A/75 W	12 V/4.17 A/50 W
VI-J22-01	J22-CY	21-56 V/2.08 A/75 W	15 V/3.33 A/50 W
VI-J22-04	J22-CY	21-58 V/1.72 A/62 W	15 V/2.53 A/38 W
VI-J24-05	J24-EY	18-64 V/2.08 A/75 W	48 V/1.0 A/48 W
VI-J30-16	J30-CZ	42-60 V/0.98 A/47 W	4.5 V/5 A/22 W
VI-J30-18	J30-IY	45-53 V/0.94 A/45 W	2 V/10 A /20 W
VI-J32-02	J32-CY	42-60 V/1.56 A/75 W	15 V/3.33 A/50 W
VI-J32-05	J32-CW	45-51 V/2.81 A/135 W	15 V/6 A/90 W
VI-JN0-28	JN0-EX	36-76 V/2.08 A/100 W	5 V/15 A/75 W

<u>Model</u>	<u>Parent</u>	<u>Input (DC)</u>	<u>Output (DC)</u>
VI-JN1-03	JN1-CX	40-75 V/2.08 A/100 W	12 V/6.25 A/75 W
VI-JN1-09	JN1-EY	36-76 V/1.56 A/75 W	9 V/5.56 A/50 W
VI-JN4-01	JN4-CY	36-72 V/1.04 A/50 W	70 V/0.3 A/21 W
VI-J40-04	J40-CY	67-121 V/1.04 A/75 W	5 V/10 A/50 W
VI-J40-08	J40-CY	48-85 V/1.12 A/75 W	5 V/10 A/50 W
VI-J41-02	J41-CY	67-121 V/1.04 A/75 W	12 V/4.17 A/50 W
VI-J41-06	J41-CX	50-125 V/1.38 A/100 W	12 V/6.67 A/80 W
VI-JT1-01	JT1-IZ	45-160 V/0.5 A/50 W	12 V/2.08 A/25 W
VI-J50-05	J50-CX	80170 V/0.83 A/100 W	5 V/15 A/75 W
VI-J50-12	J50-CX	100-200 V/0.66 A/100 W	6.0 V/12.5 A/75 W
VI-J51-06	J51-CZ	100-200 V/0.33 A/50 W	10 V/2.5 A/25 W
VI-J52-04	J52-EY	85-185 V/0.5 A/75 W	15 V/3.33 A/50 W
VI-J60-04	J60-IX	200-400 V/0.33 A/100 W	6.5 V/11.5 A/75 W
VI-J60-16	J60-EW	200-400 V/0.45 A/135 W	6.5 V/15 A/98 W
VI-J61-10	J61-CW	200-400 V/0.45 A/135 W	9 V/11.11 A/100 W
VI-J61-11	J61-CX	200-400 V/0.33 A/100 W	12 V/6.25 A/75 W
VI-J61-18	J61-EX	200-400 V/0.33 A/100 W	8 V/9.38 A/75 W
VI-J71-01	J71-CY	100-375 V/0.3 A/75 W	8 V/6.25 A/50 W
VI-J71-07	J71-CZ	100-375 V/0.2 A/50 W	8 V/3.13 A/25 W
VI-J74-03	J74-CZ	100-375 V/0.2 A/50 W	60 V/0.42 A/25 W

<u>Model #</u>	<u>Parent</u>	<u>Input</u>	<u>Output</u>	<u>Change</u>
VI-201-25	201-CY	9.2-36V/6.25A/75W	12V/4.17A/50W	Input
VI-201-29	201-IX	10-20V/8.33A/100W	12V/6.25A/75W	Label
VI-20N-02	20N-CY	10-55V5.08A/61W	18V/2.0A/36W	In/Output
VI-203-27	203-CY	10-30V/6.25A/75W	24V/2.08A/50W	Input
VI-203-29	203-CY	12-36V/3.12A/75W	24V/2.08A/50W	Label
VI-211-17	211-CV	21-32V/8.335A/200W	12V/12.5A/150W	Label
VI-2WL-04	2WL-CV	18-40V/8.335A/200W	28V/6.25A/175W	Input
VI-22M-01	22M-CX	17-52V/2.36A/85W	10V/6.0A/60W	NO OTP
VI-220-23	220-23	17-52V/1.52A/55W	5V/6.0A/30W	No OTP
VI-221-21	221-CW	20-60V/3.12A/150W	12V/10.4A/125W	Label
VI-222-11	222-CX	17-52V/2.77A/100W	15V/5.0A/75W	No OTP
VI-2NY-03	2NY-CU	36-76V/3.27A/157W	3.3V/40A/132W	Label
VI-2NY-04	2NY-CW	36-76V/1.89A/91W	3.3V/20A/66W	Label
VI-2NO-29	2NO-CV	36-76V/4.16A/200W	5V/30A/150W	Label
VI-2N1-11	2N1-CU	36-76V/5.2A/250W	12V/16.7A/200W	Label
VI-2N1-12	2N1-CV	36-76V/4.16A/200W	12V/12.5A/150W	Label
VI-2N3-03	2N3-CV	32-60V/4.16A/200W	24V/6.25A/150W	Input
VI-25V-01	25V-01	100-200V/1.33A/200W	6V/25A/150W	Output
VI-253-13	253-EU	100-200V/1.67A/250W	24V/8.33A/200W	No OTP
VI-25L-05	25L-CU	70-150V/2.5A/250W	28V/7.14A/200W	Input
IP-2T1-01	2T1-01	66-140V/1.69A/169W	12V/12A/144W	Input
VI-26V-02	26V-CU	200-400V/0.83A/250W	5.8V/34.5A/200W	Label
VI-26J-03	26J-CU	200-400V/0.83A/250W	33.7V/5.93A/200W	Output
VI-264-44	264-EU	200-400V/0.83A/250W	60V/3.33A/200W	Output
VI-B01-04	B01-IX	10-20V/8.33A/100W	12V/6.25A/75W	Label
VI-B03-11	B03-CY	12-36V/3.12A/75W	24V/2.08A/50W	Label
VI-B3Z-01	B3Z-CU	42-60V/2.2A/105W	2.0V/40A/80W	Label
VI-B50-04	B50-CV	100-200V/1.33A/200W	5V/30A/150W	Label
VI-B5L-04	B5L-CU	70-150V/2.5A/250W	28V/7.14A/200W	Input
IP-BT1-01	BT1-01	66-140V/1.69A/169W	12V/12A/144W	Input
VI-B64-20	B64-EU	200-400V/0.83A/250W	60V/3.33A/200W	Output

<u>Model #</u>	<u>Parent</u>	<u>Input</u>	<u>Output</u>	<u>Change</u>
VI-203-31	250-EX	10-36V/8.33A/100W	24.0V/3.13A/75W	Input
VI-21T-01	21T-01	21-32V/10.4A/250W	6.5V/30.77A/200W	Input
VI-2N3-11	2N3-CU	36-76V/5.20A/250W	26V/7.69A/200W	Output
VI-24J-02	24J-EU	55-100V/3.47A/250W	35V/5.71A/200W	Label
VI-250-28	250-CV	100-200V/1.33A/200W	5.0V/30A/150W	Label
VI-250-29	250-CV	100-200V/1.33A/200W	5.0V/30A/150W	Label
VI-260-117	260-CU	200-400V/0.833A/250W	5.0V/40A/200W	Label
VI-264-31	264-CU	220-400V/0.83A/250W	95V/2.1A/200W	Input
VI-BN4-04	BN4-CV	36-76V/4.16A/200W	48V/3.12A/150W	Label
VI-B60-48	B60-CU	200-400V/0.833A/250W	5.0V/40A/200W	Label